

Homework 4: Information Representation

INFO/CSE 100 Autumn 2004

Print out this page and write your answers to the following questions.

Information Representation: Data Encoding

1. Example: Consider the encoding from the lecture 18 for a game of Tic-Tac-Toe.

These are the kind of answers we expect for Question 2

- (a) How many different items of information were chosen to represent the game?

3 items – empty cell or player 1 or player 2

- (b) How many positions were used?

9 positions – one per board square

- (c) How many possible game states are there?

3^9

2. Construct an encoding for a traditional chess board and chess pieces. (refer to <http://en.wikipedia.org/wiki/Chess> for a description of 8x8 board and the different kinds of pieces)

- (a) Items of information

- i. How many different items of information did you chose to represent the game?

In other words, how many distinct symbols will you need in your encoding scheme?

- ii. Write out your encoding using numbers as symbols, explaining what each number represents. Follow the example in Lecture 18, Slide 5

- (b) How many positions do you need, and why? (Follow 1(b) above)

- (c) How many possible game states are there? (You can ignore the fact that some game states cannot be reached in normal play. Include those "impossible" states in your calculation.)

Name: _____ Student ID: _____ Section: _____

Positions and Decimal, Binary, & Hexadecimal Numbers

3. Conversions (Lecture 18, slide 14 & Lecture 19, slide 5)

(a) Convert these numbers to decimal (base 10)

$$110_2 =$$

$$1101_2 =$$

$$10_{10} =$$

$$10_{16} =$$

(b) Convert these numbers to binary (base 2)

$$FF_{16} =$$

$$10_2 =$$

$$A_{16} =$$

(c) Convert these numbers to hexadecimal (base 16)

$$1_2 =$$

$$16_{10} =$$

4. Consider a number in base 5. What is the largest possible number you can represent with 4 positions? Write your answer in decimal. (hint, Lecture 19, slide 3)

5. Consider using binary bits to represent the numbers 0, 1, 2, and 3.

(a) At least how many positions are required to represent this in binary?

(b) Why are the minimum number of positions from answer 5a insufficient if you want to represent 0 and both positive and negative 1, 2, and 3?