CSE 451: Operating Systems Spring 2010


Module 12.5 Secondary Storage

John Zahorjan zahorjan@cs.washington.edu Allen Center 534

Secondary storage

- Secondary storage typically:
 - is anything that is outside of "primary memory"
 - does not permit direct execution of instructions or data retrieval via machine load/store instructions
- Characteristics:
 - it's large: 250-2000GB
 - it's cheap: \$0.08/GB
 - it's persistent: data survives power loss
 - it's slow: milliseconds to access
 - why is this slow??
 - it *does* fail, if rarely
 - Or not so rarely these days...

Another trip down memory lane ...




05/17/10

Disk trends

- Disk capacity, 1975-1989
 - doubled every 3+ years
 - 25% improvement each year
 - factor of 10 every decade
 - Still exponential, but far less rapid than processor performance
- Disk capacity since 1990
 - doubling every 12 months
 - 100% improvement each year
 - factor of 1000 every decade
 - 10x as fast as processor performance!

- Only a few years ago, we purchased disks by the megabyte (and it hurt!)
- Today, 1 GB (a billion bytes) costs \$1,\$0.50 from Dell (except you have to buy in increments of 40 80 GB)
 - => 1 TB costs \$1K \$500, 1 PB costs \$1M \$500K
- In 3 2 years, 1 GB will cost \$.10
 > 1 TB for \$100, 1 PB for \$100K


Memory hierarchy



• Each level acts as a cache of lower levels

05/17/10

Memory hierarchy: distance analogy



05/17/10

Disks and the OS

- Disks are messy, messy devices
 - errors, bad blocks, missed seeks, etc.
- Job of OS is to hide this mess from higher-level software
 - low-level device drivers (initiate a disk read, etc.)
 - higher-level abstractions (files, databases, etc.)
- OS may provide different levels of disk access to different clients
 - physical disk block (surface, cylinder, sector)
 - disk logical block (disk block #)
 - file logical (filename, block or record or byte #)

Physical disk structure

- Disk components
 - platters
 - surfaces sector track – tracks - sectors surface – cylinders – arm heads cylinder platter arm head

Disk performance

- Performance depends on a number of steps
 - seek: moving the disk arm to the correct cylinder
 - depends on how fast disk arm can move
 - seek times aren't diminishing very quickly (why?)
 - rotation (latency): waiting for the sector to rotate under head
 - depends on rotation rate of disk
 - rates are increasing, but slowly (why?)
 - transfer: transferring data from surface into disk controller, and from there sending it back to host
 - depends on density of bytes on disk
 - increasing, and very quickly
- When the OS uses the disk, it tries to minimize the cost of all of these steps
 - particularly seeks and rotation

05/17/10

Disk scheduling

- Seeks are very expensive, so the OS attempts to schedule disk requests that are queued waiting for the disk
 - FCFS (do nothing)
 - reasonable when load is low
 - long waiting time for long request queues
 - SSTF (shortest seek time first)
 - minimize arm movement (seek time), maximize request rate
 - unfairly favors middle blocks
 - SCAN (elevator algorithm)
 - service requests in one direction until done, then reverse
 - skews wait times non-uniformly (why?)
 - C-SCAN
 - like scan, but only go in one direction (typewriter)
 - uniform wait times

05/17/10

Interacting with disks

- In the old days...
 - OS would have to specify cylinder #, sector #, surface #, transfer size
 - i.e., OS needs to know all of the disk parameters
- Modern disks are even more complicated
 - not all sectors are the same size, sectors are remapped, ...
 - disk provides a higher-level interface, e.g., SCSI
 - exports data as a logical array of blocks [0 ... N]
 - maps logical blocks to cylinder/surface/sector
 - OS only needs to name logical block #, disk maps this to cylinder/surface/sector
 - on-board cache
 - as a result, physical parameters are hidden from OS
 - both good and bad

05/17/10